



## PERFORM 3000

PORTABLE POWER

Generating Sets Range PERFORM

### PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- KOHLER air-cooled industrial engine
- Compact frame with protection panels against shocks
- Good value for money
- Starting up facilitated thanks to the summer/winter positions

**QUAD CLEAN AIR FILTER** The Cyclonic Quad Clean air filters provide 4 levels of filtration which effectively filter out large particles and capture the finest particles. They ensure a continuous supply of clean air to the engine, fuel economies, increase the engine performance and extend its lifetime

### Range PERFORM

An efficient, cost effective and easy to handle equipment, suitable for frequent use.



## PERFORM 3000

### GENERAL SPECIFICATIONS

Range	PERFORM
Frequency (Hz)	50 Hz
Max power (kW) *	2,80
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	4,10
75% cons. (l/h) *	1,30
75% Autonomy (h) *	3,20
Sound power level guaranteed LwAdB(A)	96
Acoustic pressure level @1m in dB(A)	81
Acoustic pressure level @7m in dB(A)	67

### ENGINE SPECIFICATIONS

Engine brand	KOHLER
Engine type	CH270
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm3)	208
Oil system capacity including filters (L)	0,60

### ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

### DIMENSIONS AND WEIGHT

Length (cm)	65
Width (cm)	51
Height (cm)	46
Dry Weight (kg)	45

### PACKAGING

Packaging type	Box
Length (cm)	66
Width (cm)	52,50
Height (cm)	47
Weight (kg)	47
Pallet type	140/110
Number of box by pallet	12
Pallet height (cm)	154
weight of the packaged Pallet (kg)	580



PERFORM 3000 - PORTABLE POWER - Generating Sets PERFORM

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com

11/06/2019

### ACCESSORIES SUPPLIED



Funnel

Floor maintaining slot



User and maintenance manual



Ergonomic handle grip

### OPTIONS



**R01**

This set includes the hour meter and the differential circuit breaker.



**R05M**

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



**RKB1HD**

Trolley kit for the generating sets of 6kW or below



**RKS1**

Maintenance kit for KOHLER CH270 engine.



**RHO**

Cover for SDMO 's generating sets, welding sets and water pumps



**RPM**

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V



**RPQ**

For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm<sup>2</sup> cable.



**RBAC**

Removable storage box



**RKD1**

kit of two diferential removable adapters for domestic sockets. Schema for ground bonding with isolated neutral