

DIESEL 6000 E XL C5

PORTABLE POWER

Generating Sets Range DIESEL

PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- KOHLER air-cooled industrial engine
- Large Autonomy
- Comfort of prehension thanks to the ergonomic handles
- Electric starter with batteries without maintenance

OIL SAFETY Thanks to this functionality, the engine will not start or will stop during its functioning if the oil level for gasolines or the oil pressure for diesels is too low : your generating set is perfectly protected !
STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

Range DIESEL

Both long run times and very long life for professional applications.



DIESEL 6000 E XL C5

GENERAL SPECIFICATIONS

Range	DIESEL
Frequency (Hz)	50 Hz
Max power (kW) *	4,90
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Diesel Fuel
Tank (L)	16
75% cons. (l/h) *	1,20
75% Autonomy (h) *	13,30
Sound power level guaranteed LwAdB(A)	108
Acoustic pressure level @1m in dB(A)	93
Acoustic pressure level @7m in dB(A)	79

ENGINE SPECIFICATIONS

Engine brand	KOHLER DIESEL
Engine type	KD15-440E_C5
Distribution	Diesel O.H.V.
Start	Electrical
Oil shutdown	Oui
Displacement (cm3)	442
Oil system capacity including filters (L)	1,50

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 32A socket- circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	81
Width (cm)	55,50
Height (cm)	59
Dry Weight (kg)	103

PACKAGING

Packaging type	Box
Length (cm)	82
Width (cm)	56,50
Height (cm)	60
Weight (kg)	106
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	193
weight of the packaged Pallet (kg)	646

KOHLER®

SDMO®

DIESEL 6000 E XL C5

ACCESSORIES SUPPLIED



User and maintenance manual



Floor maintaining slot



Ergonomic handle grip



Battery without maintenance

OPTIONS



R02

This set includes the hour meter and the differential circuit breaker.



R05M

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



RKB1HD

Trolley kit for the generating sets of 6kW or below



RH1

Cover for SDMO 's generating sets, welding sets and water pumps



RPM

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V



RPQ

For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.

KOHLER®

SDMO®

25/06/2019

DIESEL 6000 E XL C5 - PORTABLE POWER - Generating Sets DIESEL

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com