

KOHLER

SDMO



HXC 4000 C5

PORTABLE POWER

Generating Sets Range INTENS

PRODUCT ADVANTAGES

- Entire group guaranteed 3 years
- HONDA Professional Engine
- Solid and high-performance equipment

STAGE V (2016/1628 EU) : This product is compliant with regulation for implementing requirements relating to gaseous and pollutant emission limits in Europe

Range INTENS

Equipment that is robust, long-lasting and simple to use for repetitive operations in difficult conditions.



HXC 4000 C5

GENERAL SPECIFICATIONS

Range	INTENS
Frequency (Hz)	50 Hz
Max power (kW) *	3,70
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	5,30
75% cons. (l/h) *	2,10
75% Autonomy (h) *	2,50
Sound power level guaranteed LwA dB(A)	102
Acoustic pressure level @1m in dB(A)	86
Acoustic pressure level @7m in dB(A)	72

ENGINE SPECIFICATIONS

Engine brand	HONDA
Engine type	GX270_C5
Distribution	O.H.V.
Start	Starter
Oil shutdown	Oui
Displacement (cm ³)	270
Oil system capacity including filters (L)	1,10

ALTERNATOR SPECIFICATIONS

Technology	Brushless
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

PLUGS AND PANEL DESCRIPTIVE

2 230V 10/16A sockets - circuit breaker

DIMENSIONS AND WEIGHT

Length (cm)	71,50
Width (cm)	57
Height (cm)	49
Dry Weight (kg)	56

PACKAGING

Packaging type	Box
Length (cm)	73
Width (cm)	58
Height (cm)	49,50
Weight (kg)	58,50
Pallet type	120/80
Number of box by pallet	6
Pallet height (cm)	162
weight of the packaged Pallet (kg)	361

KOHLER

SDMO

26/09/2019

HXC 4000 C5 - PORTABLE POWER - Generating Sets INTENS


This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com

ACCESSORIES SUPPLIED



Funnel



User and maintenance manual

OPTIONS



R01

This set includes the hour meter and the differential circuit breaker.



R05M

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



RKB2

Trolley kit for the generating sets superior to 6kW



RH1

Cover for SDMO 's generating sets, welding sets and water pumps



RPM

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V



RPQ

For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.