



XP-K6M-ALIZE

PORTABLE POWER

Generating Sets Range INDUSTRIAL

PRODUCT ADVANTAGES

- KOHLER water-cooled industrial engine
- Entire group guaranteed 3 years
- complete control panel
- Low noise level
- Large Autonomy

Range INDUSTRIAL

Leading edge technology, designed for regular, intensive use, that is powerful and quiet.



XP-K6M-ALIZE

GENERAL SPECIFICATIONS

Range	INDUSTRIAL
Frequency (Hz)	50 Hz
Voltage (V)	230 single phase
Standard Control Panel	APM303
Tank (L)	50
Sound power level guaranteed LwA dB(A)	83
Acoustic pressure level @1m in dB(A)	67
Acoustic pressure level @7m in dB(A)	54

POWER

Voltage (V)	ESP		PRP		Intensity(A)
	kWe *	kVA *	kWe *	kVA *	
230 single phase	5,50	5,50	5	5	24

ENGINE SPECIFICATIONS

Engine brand	KOHLER KDI
Engine ref.	KDW1003
Air inlet system	Athmo
Cylinders configuration	L
Number of cylinders	3
Displacement (L)	1,03
Bore (mm)	75
Stroke (mm)	77,60
Compression ratio	22,8 : 1
Speed (RPM)	1500
Pistons speed (m/s)	3,88
Maximum stand-by power at rated RPM (kW)	8,50
Frequency regulation, steady state (%)	+/- 2.5%
Governor type	Mechanical
Consumption @ 75% PRP load (L/h) *	1,90
Oil system capacity including filters (L)	2,40
Oil consumption 100% ESP 50Hz (L/h)	0,04

ALTERNATOR SPECIFICATIONS

Alternator commercial brand	KOHLER
Alternator ref.	KH00260T
Voltage regulation at established rating (+/- %)	1

PLUGS AND PANEL DESCRIPTIVE

1 230V 10/16A socket - circuit breaker + 1 230V 16A socket - circuit breaker + 1 230V 32A socket - circuit breaker+ Residual Current Device 30 mA + APM202

DIMENSIONS AND WEIGHT

Length (cm)	150
Width (cm)	76
Height (cm)	103
Dry Weight (kg)	390



25/07/2019

XP-K6M-ALIZE - PORTABLE POWER - Generating Sets INDUSTRIAL

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. *ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com

ACCESSORIES SUPPLIED



User and maintenance manual

OPTIONS



CA308

ERR: not found in dict valeurs



VERSO-M

Automatic start up on lack of power (included engine preheating, battery charger, normal/back up reverser)



R05M

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



RMS

Commissioning : compliance checks of the installation, level controles, starting, no-load and load test, Instruction of the customer on the maintenance of the genset.

Adaptor for industrial sockets

ERR: not found in dict valeurs



RBH1

Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40)



RBH0-5

Box of 24 0.5L cans of oil or 20 1 L cans of oil (SAE 15W40).



RPM

Male plugs for all models made up of : 2 x 16 A/230 V, EEC17: 1 x 16A/230 V, 1 x 32A/230 V and 1 x 16A/400V



RPQ

For earthing your generator set. Galvanised 1 m long spike, supplied with 2 m of 10 mm² cable.