



## INVERTER PRO 3000 E PrIndus

PORTABLE POWER

Generating Sets Range PRESTIGE

### PRODUCT ADVANTAGES

- Ergonomic, light and compact equipment
- Very Silent
- 12 V output
- Quality current
- Low consumption

**INVERTER TECHNOLOGY** This new, very high performance technology guarantees the stability of the voltage and frequency of your genset to within  $\pm 1\%$  of the nominal value. Such high precision makes it possible to produce high-quality current and supply the most demanding equipment.

**12V OUTPUT** Supplies equipment operating off 12V and in particular for recharging batteries. Connection cables are included.

### Range PRESTIGE

Top of the range equipment that is efficient and with low noise emissions, for a wide range of standard requirements.

## INVERTER PRO 3000 E PrIndus

### GENERAL SPECIFICATIONS

Range	PRESTIGE
Frequency (Hz)	50 Hz
Max power (kW) *	3
Nominal voltage (V)	230
Number of Phase	Single phase
Fuel	Petrol
Tank (L)	13
75% cons. (l/h) *	1,30
75% Autonomy (h) *	10
Sound power level guaranteed LwA dB(A)	88
Acoustic pressure level @1m in dB(A)	73
Acoustic pressure level @7m in dB(A)	59

### ENGINE SPECIFICATIONS

Engine brand	YAMAHA
Engine type	MZ175
Distribution	O.H.V.
Start	Electrical Starter
Oil shutdown	Oui
Displacement (cm <sup>3</sup> )	171
Oil system capacity including filters (L)	0,60

### ALTERNATOR SPECIFICATIONS

Technology	Inverter
AVR Regulation	No
Indication of protection	IP 23
Insulation class	H

### PLUGS AND PANEL DESCRIPTIVE

2 sockets 230V 16A - circuit breaker + 1 socket 12V 12A - circuit breaker + indicator

### DIMENSIONS AND WEIGHT

Length (cm)	68
Width (cm)	44,50
Height (cm)	55,50
Dry Weight (kg)	68

### PACKAGING

Packaging type	Box
Length (cm)	74,10
Width (cm)	55,10
Height (cm)	63,70
Weight (kg)	78
Pallet type	
Number of box by pallet	2
Pallet height (cm)	68
weight of the packaged Pallet (kg)	167



INVERTER PRO 3000 E PrIndus - PORTABLE POWER - Generating Sets PRESTIGE

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com

13/01/2020





# INVERTER PRO 3000 E PrIndus

## ACCESSORIES SUPPLIED



Spark plug spanner



User and maintenance manual

## OPTIONS



**R05M**

The manual changeover switch is used to connect and disconnect a generating set manually to a domestic circuit when there is a power cut.



**RYS3**

Maintenance kit for YAMAHA MZ175 engine.



**RAP**

The adaptor for industrial sockets is used to connect 230-V appliances to the industrial socket.



13/01/2020

INVERTER PRO 3000 E PrIndus - PORTABLE POWER - Generating Sets PRESTIGE

This document is not contractual - The SDMO company reserves the right to modify any of the characteristics stated in this document without notice, in a constant effort to improve the quality of its products. \*ISO 8528.

SDMO Industries - 270 rue de Kerervern - CS 40047 - 29801 Brest cedex 9 - France - Tél. +33 (0)2 98 41 41 41 - www.kohlersdmo.com